



## EJ-T

### Affordable

The EJ-T injects 2-way telephone line audio into a PA system. Simply hook-up the EJ-T between the telephone outlet on the wall and the base of the phone, then make a connection between the output of the EJ-T and either a mic level input (requires 16-EJTM cable), or a line level input connection to a PA system.

### Active Circuitry

The EJ-T provides an affordable solution for distance learning in the classroom, simple teleconferencing in a boardroom, or broadcasting a teleconferenced call over a PA system in an auditorium.

### Compact

The EJ-T can also be used as an interface to record a telephone conversation. Just connect the output to a recording device.

The EJ-T is an active device, and comes with its' own 9VDC power supply.

## Specifications:

Inputs . . . . .	RJ-11 Modular Telephone Jacks
Output . . . . .	3.5mm Mono Jack
Output Signal . . . . .	Transformer balanced line level
Frequency Response . . . . .	20Hz to 20kHz
Power Requirement . . . . .	9VDC 100mA
Package . . . . .	Steel case with black powdercoat finish
Dimensions (L x W x H) . . . . .	.3.75" x 2.5" x 1.25"
Weight . . . . .	8 oz.

## EJ-T Accessory Cables:

### For Line Level Input to PA System

- 16-095**      3 ft. 3.5mm Male to 3.5mm Male. For when line level input connection is a 3.5mm Jack.
  
- 16-135**      5 ft. 3.5mm Stereo Male to Dual RCA Males. For when line level input connection is RCA Jacks.
  
- 16-305**      5 ft. 3.5mm Male to 1/4" Phono Jack. For when line level input connection is a 1/4" Phono Jack.

### For Mic Level Input to PA System

- 16-EJTM**      Unbalanced Line Level to Unbalanced Mic Level via 6 ft. 3.5mm Male to 3-Pin XLR Male.

## Warranty:

Emtech Electronics, Inc. warrants the Model EJ-T for a period of two years, from the original date of purchase, against defects in parts and workmanship. If a defect occurs, the unit will be repaired or replaced, at our option, free of all charges if delivered prepaid to the factory. Warranty does not extend to finish, appearance, abuse or defects due to the misuse or operation under other than specified conditions, nor does it extend to incidental or consequential damages. Repair by anyone other than Emtech will void the warranty.

©Emtech Electronics, Inc. 1126 No. 1200 West Orem, UT 84057 1-866-200-2878  
[www.emtechelectronics.com](http://www.emtechelectronics.com)