



MULTI-ADAPTER MODEL EJ-8

handles virtually
any input signal

includes all audio
connections

no power supply
required

wider frequency
range & stronger
output signal

The Model EJ-8 is a multi-input adapter that accepts multiple line level inputs from a wide variety of audio/video devices for input into an existing PA or music system, while providing the necessary matching and isolation for protecting the system. The EJ-8 also acts as a mixer when accepting signals from more than one source at the same time.

The EJ-8 is similar to the EJ-10 except it does not have telephone line capability. Without the telephone line capability, the output signal from the EJ-8 is 22dB higher than the EJ-10. It also has a wider frequency range (20-20K Hz), and a more affordable price for those who do not need to have the telephone capability.

The EJ-8 comes with everything required to connect virtually any audio source to the microphone input of an existing sound system.

The EJ-8 is a completely passive device, no batteries or external power sources are required for operation.

The EJ-8 features a volume control, phone and phono jacks, binding posts, and a hum switch. An assortment of interconnect cables and a nylon carrying case come attached to the EJ-8. A complete instruction manual comes stored in a pocket of the carrying case.

Specifications:

Inputs	Unbalanced line level / Speaker level (connections include mono/stereo phone, mono mini-phone, RCA phono jacks, and bare wire binding posts)
Output	Transformer balanced adjustable mic level (3' cable with male XLR plug)
Attenuation	Line levels = -20dB to -100dB Speaker level = -35dB to -100dB
Frequency Response	20Hz to 20kHz
Package	Steel case with polycarbonate overlay in black Cordora nylon pouch with zipper
Dimensions (L x W x H)	6.6" x 2.5" x 3"
Weight	1 lb. 12 oz.

Architects'/Engineers' Specifications:

The multi-Adapter box will accept mono or stereo line and speaker level inputs; converting all of the signals to a transformer balanced mic level output. The adapter box must have an adjustable output control, and a hum removal switch. All interconnect cables must be attached to the unit, and a padded zippered case must be provided for protection and for transportation. An operations manual must be provided and stored in the carrying case. The size of the adapter box must be 6.6" L x 2.5" W x 3.0" H, and its' weight should be 1 lb. 12 oz. The multi-adapter box must be an Emtech Model EJ-8.

Warranty:

Emtech Electronics, Inc. warrants the Model EJ-8 for a period of two years, from the original date of purchase, against defects in parts and workmanship. If a defect occurs, the unit will be repaired or replaced, at our option, free of all charges if delivered prepaid to the factory. Warranty does not extend to finish, appearance, abuse or defects due to the misuse or operation under other than specified conditions, nor does it extend to incidental or consequential damages. Repair by anyone other than Emtech will void the warranty.

©Emtech Electronics, Inc. 1126 No. 1200 West Orem, UT 84057 1-866-200-2878
www.emtechelectronics.com